



Fuse-link, high speed, 400 A, AC 690 V, 200 kA, DIN 1, aR, DIN, IEC, type T indicator, live gripping lugs

Part no. **FUSE 400A 690V aR DIN 1 HSDNH**  
 Catalog No. **170M3819D**

Similar to illustration

### Delivery program

|                              |   |    |                                       |
|------------------------------|---|----|---------------------------------------|
| Product range                |   |    | Fuse                                  |
| Basic function               |   |    | Fuse-link                             |
| Field of application         |   |    | high speed                            |
| Rated current                | I | A  | 400                                   |
| Rated voltage                |   |    | AC 690 V                              |
| Construction size            |   |    | DIN 1                                 |
| Utilization category         |   |    | aR                                    |
| Status indicator             |   |    | type T indicator                      |
| Description                  |   |    | live gripping lugs                    |
| Breaking Capacity            |   | kA | 200                                   |
| usable for size/applications |   |    | semiconductor protection              |
| Standard/Approval            |   |    | DIN<br>IEC                            |
| Shape                        |   |    | square body with knife blade contacts |
| Standards/Regulations        |   |    | DIN 43620<br>IEC 60269-4              |

### Technical data ETIM 8.0

|  |  |    |   |
|--|--|----|---|
| Circuit breakers and fuses (EG000020) / HRC fuse (EC004556)  |  |    |   |
| Electric engineering, automation, process control engineering / Electrical installation, device / Safety fuse inserts / Safety fuse inserts (unspecified) (ecl@ss10.0.1-27-14-20-90 [BAB264011]) |  |    |   |
| Fuse construction type according to IEC 60269  |  |    | 1   |
| Type of current  |  |    | AC  |
| Rated voltage AC   |  | V  | 690                                       |
| Rated voltage DC   |  | V  |   |
| Rated current  |  | A  | 400                                       |
| Utilization category   |  |    | aR (accompanied semiconductor protection) |
| Breaking capacity  |  | kA | 200                                       |
| Colour code  |  |    | None                                      |
| Type of fuse status indicator  |  |    | Combination fuse status indicator         |
| Power loss at rated current  |  | W  | 60  |
| Mounting holes   |  |    |   |
| Centre-to-centre distance of connections   |  | mm |   |