

High Power, DC Pass

Power Splitter/Combiner

ZN2PD-9G-S+

2 Way-0° 50Ω 30W 1700 to 9000 MHz

The Big Deal

- Wideband, 1700 to 9000 MHz
- High power, up to 30W as a splitter
- Low insertion loss, 0.5 dB
- Low unbalance, 0.1 dB, 1°
- High isolation, 22 dB



CASE STYLE: VVV180

Product Overview

Mini-Circuits' ZN2PD-9G-S+ is a 2-way 0° high-power splitter/combiner providing up to 30W power handling as a splitter (0.8W as a combiner) and low insertion loss across the 1700 to 9000 MHz frequency range. Its outstanding combination of high power handling and low loss minimize power dissipation and provide excellent signal power transmission from input to output. The ZN2PD-9G-S+ comes housed in a rugged aluminum alloy case measuring 1.8 x 1.75 x 0.65" with SMA connectors.

Key Features

Feature	Advantages
Wideband, 1700 to 9000 MHz	This model supports bandwidth requirements for a wide variety of applications.
High power handling: <ul style="list-style-type: none">• 30W to 5800 MHz• 20W to 9000 MHz	The ZN2PD-9G-S+ is suitable for systems with a wide range of power requirements.
Low insertion loss, 0.5 dB	The combination of 30W power handling and low insertion loss makes this model a suitable candidate for distributing signals while maintaining excellent transmission of signal power.
Low unbalance: <ul style="list-style-type: none">• 0.1 dB amplitude unbalance• 1° phase unbalance	Produces nearly equal output signals, ideal for parallel path and multichannel systems.
High isolation, 22 dB	Minimizes interference between ports.
DC Passing, 400mA (200mA each port)	Supports applications where DC power is needed through the RF line.

Notes

- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp



Power Splitter/Combiner

ZN2PD-9G-S+

2 Way-0° 50Ω 30W 1700 to 9000 MHz



Generic photo used for illustration purposes only

CASE STYLE: VVV180

Connectors	Model
SMA	ZN2PD-9G-S+

+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

Maximum Ratings


Operating Temperature(@<30W)	-55°C to 60°C
Operating Temperature(@<10W)	-55°C to 100°C
Storage Temperature	-55°C to 100°C
DC Current	400 mA (200mA for each port)

Permanent damage may occur if any of these limits are exceeded.

Coaxial Connections

SUMPORT	S
PORT 1	1
PORT 2	2


Outline Drawing



Outline Dimensions (inch/mm)

A	B	C	D	E	F	G
1.80	1.75	.66	.125	1.675	.125	.125
45.72	44.45	16.76	3.18	42.55	3.18	3.18
H	J	K	L	M	wt	
1.625	.31	.63	1.13	.88	grams	
41.28	7.87	16.00	28.70	22.35	65.2	

Electrical Schematic



Features

- very wideband, 1700 to 9000 MHz
- low insertion loss, 0.5 dB typ.
- good isolation, 22 dB typ.
- up to 30W power input as splitter
- excellent amplitude unbalance, 0.1 dB typ.
- excellent phase unbalance, 1 deg. typ.
- rugged shielded case

Applications

- UHF/VHF
- PCS/DCS
- defense & federal communications
- wireless

Electrical Specifications at 25°C




Parameter	Frequency (MHz)	Min.	Typ.	Max.	Unit
Frequency Range		1700		9000	MHz
Insertion Loss (above theoretical 3 dB)	1700-6800	—	0.5	1.2	dB
	6800-9000	—	1.0	1.4	
Isolation	1700-6800	15	19		dB
	6800-9000	17	22		
Phase Unbalance	1700-6800	—	1.0	3.5	Degree
	6800-9000	—	2.0	4.0	
Amplitude Unbalance	1700-6800	—	0.15	0.4	dB
	6800-9000	—	0.2	0.6	
VSWR (Port S)	1700-6800	—	1.5		dB
	6800-9000	—	1.7		
VSWR Output (Port 1-2)	1700-6800	—	1.4		dB
	6800-9000	—	1.6		
Power Handling³	As Splitter¹	1700-6800	—	30	Watt
		6800-9000	—	20	
	As Combiner²	1700-9000	—	0.8	

1. All outputs must terminate 50 ohm (VSWR 1.5:1 or better)
2. As a combiner of non-coherent signals, max. power per port is 0.8 watt power rating divided by number of ports.
3. Alternative heat sinking and heat removal must be provided by the user to limit maximum base-plate temperature to 60°C, in order to ensure proper performance. For reference, this requires thermal resistance of user's external heat sink to be 10°C/W.

Typical Performance Data

Frequency (MHz)	Total Loss ¹ (dB)		Amplitude Unbalance (dB)	Isolation (dB)	Phase Unbalance (deg.)	VSWR S	VSWR 1	VSWR 2
	S-1	S-2						
1700.00	3.42	3.41	0.01	17.93	0.12	1.47	1.11	1.11
2200.00	3.31	3.33	0.02	27.76	0.12	1.15	1.06	1.06
2700.00	3.42	3.41	0.01	24.71	0.27	1.20	1.15	1.14
3700.00	3.70	3.70	0.00	20.67	0.32	1.66	1.42	1.41
4200.00	3.69	3.68	0.01	23.57	0.43	1.60	1.40	1.40
4700.00	3.57	3.54	0.03	29.47	0.39	1.38	1.30	1.32
5200.00	3.52	3.51	0.01	46.41	0.43	1.23	1.20	1.22
5700.00	3.57	3.57	0.00	28.00	0.49	1.17	1.12	1.15
6200.00	3.63	3.62	0.01	23.68	0.52	1.21	1.13	1.15
6700.00	3.62	3.64	0.02	24.46	0.28	1.28	1.12	1.12
7200.00	3.61	3.62	0.01	23.63	0.44	1.26	1.18	1.16
7700.00	3.70	3.65	0.05	28.05	0.68	1.24	1.18	1.11
8200.00	3.79	3.76	0.03	25.09	0.72	1.27	1.27	1.19
8700.00	3.87	3.81	0.06	28.49	1.10	1.30	1.42	1.33
9000.00	3.86	3.88	0.03	28.80	0.94	1.30	1.45	1.41

1. Total Loss = Insertion Loss + 3dB splitter loss.



Notes

- Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
- Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
- The parts covered by this specification document are subject to Mini-Circuit's standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuit's website at www.minicircuits.com/MCLStore/terms.jsp

